

DATASHEET

RIGHT ANGLE WR90 WG-COAX ADAPTER								
MODEL NUMBER	WG SIZE	FREQ. (GHz)	INSERTION LOSS (dB)	VSWR MAX	FLANGE	CONNECTOR	CW POWER (W)	PEAK POWER (kW)
WGC90A-F6-C3-IT1	WR90	8.20-12.4	0.2	1.15	COVER	TYPE N F	50	1
WGC90A-F6-C1-IT1	WR90	8.20-12.4	0.2	1.15	COVER	SMA F	50	1

