



E-MPA 67-87 16 14
Medium Power Amplifier 67-87 GHz

Part-No.: 03100034

Product Description

This **E-MPA 67-87 16 14** operates in the frequency range 67 to 87 GHz.



Technical Specifications	
RF Frequency [GHz]	67 - 87
RF Port	WR12 (UG387/UM)
Gain [dB (typ)]	16
Return Loss [dB (typ)]	4
Psat [dB (typ)]	14
DC Voltage	+7 VDC
Max. Input Power	
Max. DC Voltage	+9 VDC
Max. Case Temperature	+45 °C



Typical Performance

Saturated Output Power S/N 100002

